Sharp GX15

Setup guide



For help or assistance please contact us. In New Zealand, phone 777 free from your mobile or 0800 800 021 Phone +64 9 357 5198 from Overseas (except Australia) Phone, toll free, +800 777 000 21 from Australia Or visit www.vodafone.co.nz

Setting up Vodafone Live Access

Please remember to

and back on again

after you have

in the phone.

switch your phone off

changed any settings

• Press the **Menu** key to enter the menu system.

- Scroll to **Network** and press **Select**.
- Scroll to WAP Settings and press Select.
- Highlight the next available profile and press the **Menu** key.
- Press the **Menu** key to select **Profile Name**.
- Enter Vodafone GPRS and press the Menu key.
- Scroll to IP Address and press the Menu key.
- Enter 172.030.038.003 and press the Menu key.
- Scroll to **Homepage** and press the **Menu** key.
- Enter http://live.vodafone.co.nz (case sensitive) and press the Menu key.
- Scroll to Port Number and press the Menu key.
- Change the Port Number to 09201 and press the Menu key.
- Scroll to Connection Type and press the Menu key.
- Scroll to GPRS and press the Menu key.
- Scroll to GPRS Settings and press the Menu key.
- Scroll to APN and press the Menu Key.
- Enter live.vodafone.com and press the Menu key.
- Press the **Back** key twice to return to the **WAP Settings** menu.
- Scroll to the profile you just created and press the **Menu** key.

Setting up WAP CSD Access

- Press the **Menu** key to enter the menu system.
- Scroll to Network and press Select.
- Scroll to WAP Settings and press Select.
- Highlight the next available profile and press the **Menu** key.
- Press the Menu key to select Profile Name.
- Enter Vodafone CSD and press the Menu key.
- Scroll to IP Address and press the Menu key.
- Enter 172.030.038.003 and press the Menu key.
- Scroll to Homepage and press the Menu key.
- Enter http://wap.vodafone.co.nz (case sensitive) and press the Menu key.
- Scroll to Port Number and press the Menu key.
- Change the Port Number to 09201 and press the Menu key.
- Scroll to Connection Type and press the Menu key.
- Scroll to CSD and press the Menu key.
- Scroll to CSD Settings and press the Menu key.
- Scroll to Phone No. and press the Menu key.
- Enter +6421700747 and press the Menu key.
- Leave the Username and Password blank.
- Press the **Back** key twice to return to the **WAP Settings** menu.
- Scroll to the profile you just created and press the Menu key.
- ONLY DO THIS STEP IF YOU WANT TO USE CSD AS YOUR MAIN CONNECTION METHOD.

2 CONFIGURING THE SHARP GX15 FOR PXT

vodafone

Setting up PXT access

- Press the Menu key to enter the menu system.
- Scroll to Network and press Select.
- Scroll to WAP Settings and press Select.
- Highlight the next available profile and press the **Menu** key.
- Press the Menu key to select Profile Name.
- Enter Vodafone MMS and press the Menu key.
- Scroll to IP Address and press the Menu key.
- Enter 172.030.038.003 and press the Menu key.
- Scroll to Homepage and press the Menu key.
- Enter http://pxt.vodafone.net.nz/pxtsend (case sensitive) and press the Menu key.
- Scroll to Port Number and press the Menu key.
- Change the **Port Number** to **09201** and press the **Menu** key.
- Scroll to Connection Type and press the Menu key.
- Scroll to GPRS and press the Menu key.
- Scroll to GPRS Settings and press the Menu key.
- Scroll to APN and press the Menu Key.
- Enter live.vodafone.com and press the Menu key.
- Press the Back key twice to return to the WAP Settings menu.
- Scroll to the profile you just created and press the Menu key.

To send a PXT

- Press the Menu button. Scroll to Messaging and press select.
- Scroll to Multimedia message. Press select.
- Scroll to Create message. Press select.
- To add a picture to your MMS, press Options and select picture.
- Scroll to **Photos** and press **Open**.
- Scroll to the photo you want and select **Options**. Select **Insert**.
- Enter your text or continue by pressing Options.
- You can now Send to number or Send to email.